

537Wh

Battery Capacity

600W (Max 1200W)

AC Output Power

PD60W

Type-C

Output

AC/DC/USB/PD

CHARGING

Type-C and Adapter Charging Simultaneously
Efficient Charging


iRicesPower · Empowers Better Life









OUTPUT SOCKET IS OPTIONAL

Product Name	Portable Power Station PH0087
Battery Type	Lithium iron phosphate battery
Battery Capacity/Energy	168000mAh/ 3.2V ; 537.6Wh/ 22.4V
Input :	
Solar Panel/ Car Charger/DC 6530 Port	10V~30V(90W Max)
Type-C	5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (PD 60W)
Output :	
USBA1	5V/3A,9V/2A,12V/1.5A (QC18W)
USBA2/USBA3	5V/2.4A
USBA1+USBA2+USBA3	Total output 5V/3A
Type-C	5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (PD 60W)
AC Output	100V 50Hz/60Hz (600W Max)
Car Charger Output & DC(5525)	12V/10A (120W Max)
LED Lights	Lighting/SOS/Flashing
Product Size	L327mm x W160mm x H181mm

Dongguan iRice Electronics Development Co;Ltd.

 info@iricespower.com
  +86 15818781249
  <https://iricespower.com>
 No.17, Butterfly 1st Road, Tianxin Village, Huang jiang Town, Dongguan City, China
